

## HIGH EFFICIENCY 10KW FM TRANSMITTER EM 10000 HE DIG PLUS



The 10KW FM transmitter **EM 10000 HE DIG PLUS** has been created for high efficiency transmitters. It consists on the FMA 10000 HE power amplifier with >73% efficiency and the EM 100 DIG PLUS transmitter. This high efficiency 10KW amplifier is composed by three 3-3.5KW amplifying units (FMA 3000 HE) and it has an approximate consumption of 14.2kVA, so it pays for itself in a short period of time due to its low consumption. This transmitter can be supplied with the following options:

- Stereo generator
- RDS
- Web server/SNMP telemetry
- AES/EBU digital audio input

## MAIN ADVANTAGES

- Typical AC efficiency >73% and typical RF efficiency of 80%.
- Three amplifying units each composed by four amplifying modules of 1.200W with robust LDMOS transistors of the latest technology.
- Each amplifying unit contains three independent switching power supplies connected in parallel to maintain the equipment working in case any of them fails.
- TFT screen and touch keyboard to control and to visualize operation parameters.
- Memory recording of events.
- Speed control of cooling fans according to temperature of power modules so as to optimize consumption and to decrease acoustic contamination.
- Advanced protection against load mismatches without transmission cuts and fast protection in case of excessive reflected power and/or excessive input power.
- Analog telemetry, digital remote control and telemetry RS232, remote control by opened/closed contacts.
- Low pass filter, Mains EMI filter and internal single-phase transient suppressor.
- Automatic power reduction at night when used in combination with the EM 100 DIG PLUS transmitter.
- Automatic power reduction in case of high temperature, the equipment returns automatically to its rated power value when the temperature reaches back an average value.
- Automatic power reduction in case of excessive reflected power.
- Automatic voltage control for efficiency optimization.

Cable AML, Inc. Tel: (310) 222-5599 Fax: (310) 222-5593 www.cableaml.com 20190107

## **Product Specifications**



## EM 10000 HE DIG PLUS

|                              | 07.5.400.444   |
|------------------------------|--|
| FREQUENCY RANGE              | 87.5-108MHz  |
| INPUT RETURN LOSS            | -20dB  |
| INPUT POWER                  | 100W   |
| OUTPUT POWER                 | 10KW nominal, manual and automatic   |
|                              | adjustable   |
| POWER GAIN                   | 19.2dB minimum   |
| TOTAL AC EFFICIENCY          | >73% typical   |
| RF EFFICIENCY                | 80% typical  |
| COOLING                      | Forced air, speed control of fans  |
| HARMONICS LEVEL              | -80dBc   |
| INPUT/OUTPUT IMPEDANCE       | 50Ω  |
| RF INPUT CONNECTOR           | N(F)   |
| RF OUTPUT CONNECTOR          | EIA 1+5/8"   |
| RF MONITOR CONNECTOR         | BNC(F)   |
| POWER SUPPLY                 | 230VAC ±15% 195 ÷ 265VAC, 50/60Hz;   |
|                              | or 400VAC or 230VAC three-phase  |
| CONSUMPTION                  | 14.2kVA (@10000W output power)   |
| PROTECTIONS                  | Reflected power, forward power, overdrive, and overcurrent in                          |
|                              | power modules.   |
|                              | Smart temperature protection. Ultra-fast protection against reflected and input power. |
|                              | Real time registration of events.  |
|                              | Exciter's inhibition   |
| TELEMETRY AND REMOTE CONTROL | Analog telemetry (direct and reflected power measurements).                            |
|                              | Digital telemetry and remote control RS232.  |
|                              | Remote control by opened/closed contacts.  |
| OPERATION TEMPERATURE        | -5 to +40°C  |
| WEIGHT                       | 165Kg approx. (without rack)   |
| DIMENSIONS                   | Amplifying units: 15 standard rack units of  |
|                              | 19", Control unit: 3 standard rack units of  |
|                              | 19", Switch panel: 3 standard rack units of 19"  |
| FREQUENCY RANGE              | 87.5-108MHz  |
| FM MODULATION                | 75KHz (adjustable) peak deviation. Mono  |
|                              | 180kF3E and Stereo 256kF3E   |

Cable AML, Inc. Tel: (310) 222-5599 Fax: (310) 222-5593 www.cableaml.com 20190107

| AUDIO/MPX INPUT LEVEL                   | -3.5 @ +12.5dBm @ 75KHz deviation  |
|---|--|
| AUDIO INPUT CONNECTORS                  | XLR(F)   |
| AUXILIARY CHANNEL (RDS/SCA) INPUT LEVEL | 7.5KHz deviation: -12.5 to 3.5dBm and 2KHz<br>deviation: -24 to -8dBm            |
| AUX. CHANNEL INPUT IMPEDANCE            | 10kOhm   |
| MODULATION DISTORTION                   | 7.5Khz deviation: <0.05%, 0.02% typical; 2KHz<br>deviation: <0.2%, 0.05% typical |
| S/N MONO RATIO                          | 30 to 20000Hz: >76dB, 86dB typical, CCIR: >75dB, 81dB typical                    |
| S/N STEREO RATIO                        | 30 to 20000Hz: >72dB, 77dB typical, CCIR: >68dB, 72dB typical                    |
| AUDIO CHANNELS BANDWIDTH                | 30 to 15000Hz ±0.1dB   |
| PRE-EMPHASIS TIME CONSTANT              | Selectable, 25/50/75 microseconds  |
| RF NOMINAL OUTPUT POWER                 | 100W   |
| TUNING STEPS OF TRANSMITTER             | 10/100KHz  |
| ALC OUTPUT POWER STABILITY              | ±3%  |
| SPURIOUS AND HARMONIC EMISSIONS         | <80dBc   |
| RF OUTPUT IMPEDANCE                     | 50Ω  |
| RF INPUT POWER CONNECTOR                | N  |
| RF SAMPLING CONNECTOR                   | BNC  |
| POWER SUPPLY                            | 110-230Vac ±15% 50-60Hz  |
| CONSUMPTION                             | 141VA (100W)   |
| OPERATION TEMPERATURE RANGE             | 0 to 40°C recommended, -10 to 55°C max   |
| RELATIVE HUMIDITY                       | Up to 95% without condensation   |
| DIMENSIONS                              | 484x300x90mm, 2 standard rack units of 19"                                       |
| WEIGHT                                  | 7Kg  |

Cable AML, Inc. Tel: (310) 222-5599 Fax: (310) 222-5593 www.cableaml.com 20190107